

NX-1200/1300

VHF/UHF TRANSCEIVERS

NXDN® **DMR** **DMR >>>> Auto Slot Select >>>>** **FleetSync®**

A SINGULAR SOLUTION

If you are thinking of harnessing the latest digital protocols – NXDN or DMR – to enhance business efficiency or FM analog for its simplicity, the NX-1200/1300 has you covered. Our singular solution offers the widest selection of two-way radios for everyday use. The model matrix also includes basic and keypad variations, with or without a high-contrast backlit LCD. Other features include a 7-color LED indicator and the popular KENWOOD 2-pin audio accessory connector. Plus, mixed-mode operation ensures seamless integration with legacy radios while smoothing the onward migration path to digital. But whatever your specific needs, audio quality is what determines clear voice communications – which is why KENWOOD radios are used under the most grueling conditions, like the cockpit of a racing car. Thanks to our extensive experience with professional systems, reliability is second to none. So whatever your radio requirements, KENWOOD's NX-1200/1300 offers a single platform that's right for you.



Standard Keypad & Basic Models

Features

- Multi-protocol digital radio: Designed to operate under NXDN or DMR digital and FM analog protocols
- Choose from direct & intuitive LCD with standard keypad or basic enclosures
- Easy visible Display: 8-digit LCD models featuring high-contrast, white backlit LCD
- Large 7-Color LED indicator on the top panel
 - Selective Power-on LED
 - Selective Call Alert LED
 - Battery Level Indication
 - Multi-status function indication
- RF output power 5W both on VHF/UHF
- Mixed Zone - analog and digital
- Renowned KENWOOD Audio Quality: TX/RX audio profile with optimizable digital processor
 - Audio Equalizer: Flat, High, Low
 - Auto Gain Control: On, High, Low, Off
 - Noise Suppressor
 - Microphone type settings
- Multiple Scan Functions; Dual Priority, Single Priority, Single Zone, Multi, Normal Scan
- VOX & PTT –triggered Semi- VOX, Voice-operated TX
- Emergency Function: Customizable Emergency Profile
- Lone Worker
- Max / Min Volume setting & Volume control
- Voice Announcement
- Remote Stun / Kill / Check
- Front Panel Programming Mode (for Keypad model)
- Electronic Serial Number (ESN)
- MIL-STD-810 C/D/E/F/G
- IP54 and IP55
- Intrinsically safe option (Available later)

Digital – NXDN® Mode

- FDMA – Very narrow 6.25 kHz & narrow 12.5 kHz bandwidths
- NXDN Conventional Operation
- Site Roaming
- Digital / Analog Mixed mode
- Group / Individual Call
- Status / Short data, Paging Call
- Remote Stun / Kill, Monitor, Check & Control
- Digital Bit Scrambler
- Late Entry
- Over-the-Air Alias (OAA)

Digital – DMR Mode

- TDMA 2-slot 12.5 kHz bandwidth equivalent to 6.25 kHz very narrow bandwidth
- DMR Tier II Conventional Operation
- Site Roaming
- DMR Auto Slot Select
- Dual Slot Direct Mode
- Digital / Analog Mixed mode
- Call Interruption
- Group / Individual Call
- Status / Short data, Paging Call
- Remote Stun / Kill, Monitor, Check & Control
- Enhanced Encryption (ARC4)
- Digital Bit Scrambler
- Late Entry
- Over-the-Air Alias (OAA)

Analog – FM

- FM Conventional Operation
- FleetSync: PTT ID, Stun/Revive, Talk back, Selcall
- MDC1200: PTT ID, Radio Inhibit/Uninhibit, Radio check, Emergency
- QT / DQT, DTMF, 2-tone
- Built-in Programmable Voice Inversion Scrambler (per channel)
- Built-in Compander (per channel)

Accessories

All accessories may not be available in all markets. Contact an authorized Kenwood dealer for details and complete list of all accessories.

KNB-45L
2,000mAh/7.4V
Li-Ion Battery Pack



KSC-35SK
Fast Charger
For the KNB-45L/69L
82LCM (3-Hour)



KRA-22/23
VHF/UHF Low Profile
Helical Antenna



KMC-45D
Speaker Microphone



KHS-31C
C-Ring PTT Ear
Hanger Headset



KNB-69L
2,550mAh/7.4V
Li-Ion Battery Pack



KSC-43K
Dual Chemistry
Fast Charger
For the KNB 29N/45L/69L/82LCM



KRA-26/ 27
VHF Helical Antenna
UHF Whip Antenna



KHS-26
Earbud In-line
PTT Headset



KBH-10
Belt Clip



KNB-82LCM
2,000mAh/7.4V, Intrinsically
Safe Li-Ion Battery Pack

KVC-22
DC Vehicular
Charger Adapter



KRA-41/42
VHF/UHF
Stubby Antenna



KHS-27A
D-Ring In-line
PTT Headset



Specifications

General	NX-1200	NX-1300
Pre-set Frequencies		
Type 1	136-174 MHz	450-520 MHz
Type 2		400-470 MHz
Max. Channels per Radio	260 (64 for basic model)	
Number of Zones	128 (4 for basic model)	
Max. Channels per Zone	250 (16 for basic model)	
Channel Spacing		
Analog	30*1 / 25*1 / 15 / 12.5 kHz	
Digital	12.5 / 6.25 kHz	
Power Supply	7.5 VDC ±20 %	
Battery Life	DMR	Analog/NXDN
KNB-45L (2000mAh)	Approx. 14.5 hours	Approx. 11 hours
KNB-69L (2550mAh)	Approx. 19 hours	Approx. 14 hours
Operating Temperature(Radio only)*2	-22°F to +140°F (-30°C to +60°C)	
Frequency Stability (-30 to +60°C; +25°C Ref.)	±0.5 ppm	
Antenna Impedance	50 Ω	
Dimensions	(W x H x D) Projections Not Included	
Radio with KNB-45L/82LCM	2.13 x 4.84 x 1.32 in (54 x 123 x 33.5 mm)	
Radio with KNB-69L	2.13 x 4.84 x 1.48 in (54 x 123 x 37.5 mm)	
Weight Radio Only	6.17 oz (175 g)	
Radio with KNB-45L/82LCM	10.41 oz (295 g)	
Radio with KNB-69L	10.93 oz (310 g)	
FCC ID		
Type 1	K44501000	K44501101 (pending)
Type 2		K44501100
IC Certification	282F-501000	282F-501100

*1 25 / 30 kHz in VHF/UHF Bands excluding T-Band are not included in the models sold in the USA or US territories.
*2 Operating temperature specification for a Li-Ion battery is -10°C to +60°C [14°F to +140°F].

Analog measurements made per TIA603. Specifications are measured according to applicable standards. Specifications are subject change without notice, due to advancements in technology.

Receiver	NX-1200	NX-1300
Sensitivity		
NXDN* @ 6.25 kHz Digital (3% BER)		0.18 µV
NXDN* @ 12.5 kHz Digital (3% BER)		0.22 µV
DMR* @ 12.5 kHz Digital (1% BER)		0.25 µV
DMR* @ 12.5 kHz Digital (5% BER)		0.18 µV
Analog @ 12.5/25 kHz (12 dB SINAD)		0.24 µV / 0.20 µV
Selectivity		
Analog @ 12.5 / 25 kHz		68 dB / 74 dB
Intermodulation Distortion		70 dB
Spurious Rejection		70 dB
Audio Distortion		7%
Audio Output Power		1W / 12.0 (Internal Output)

Transmitter	NX-1200	NX-1300
RF Power Output (High / Low)		5 W / 4 W / 1 W
Spurious Emission		-70 dB
FM Hum & Noise		
Analog @ 12.5 / 25 kHz		40 dB / 45 dB
Audio Distortion		2%
DMR Digital Protocol		ETSI TS 102 361-1, -2, -3
Emission Designator		16K0F3E, 11K0F3E, 8K30F1E, 8K30F1D, 8K30F7W, 4K00F1E, 4K00F1D, 4K00F7W, 4K00F2D, 7K60FXD, 7K60F7W

FleetSync® is a registered trademark of JVCケンウッド Corporation in the United States and/or other countries. NXDN® is a trademark of JVCケンウッド Corporation and Icom Inc. NEXEDGE® is a registered trademark of JVCケンウッド Corporation. All other trademarks are the property of their respective holders.

MIL-STD & IP

MIL Standard	MIL 810C Methods/Procedures	MIL 810D Methods/Procedures	MIL 810E Methods/Procedures	MIL 810F Methods/Procedures	MIL 810G Methods/Procedures
Low Pressure	5001/Procedure I	5002/Procedure I, II	5003/Procedure I, II	5004/Procedure I, II	5005/Procedure I, II
High Temperature	5011/Procedure I, II	5012/Procedure I, II	5013/Procedure I, II	5014/Procedure I, II	5015/Procedure I, II
Low Temperature	5021/Procedure I	5022/Procedure I, II	5023/Procedure I, II	5024/Procedure I, II	5025/Procedure I, II
Temperature Shock	5031/Procedure I	5032/Procedure I	5033/Procedure I	5034/Procedure I, II	5035/Procedure I
Solar Radiation	5051/Procedure I	5052/Procedure I	5053/Procedure I	5054/Procedure I	5055/Procedure I
Rain*	5061/Procedure I, II	5062/Procedure I, II	5063/Procedure I, II	5064/Procedure I, III	5065/Procedure I, III
Humidity	5071/Procedure I, II	5072/Procedure II, III	5073/Procedure II, III	5074	5075/Procedure II
Salt Fog	5091/Procedure I	5092/Procedure I	5093/Procedure I	5094	5095
Dust	5101/Procedure I	5102/Procedure I	5103/Procedure I	5104/Procedure I, III	5105/Procedure I
Vibration	5142/Procedure VIII, X	5143/Procedure I	5144/Procedure I	5145/Procedure I	5146/Procedure I
Shock	5162/Procedure I, II, V	5163/Procedure I, IV	5164/Procedure I, IV	5165/Procedure I, IV	5166/Procedure I, IV

International Protection Standard

Dust & Water Protection*

IP54/55*

To meet IP54/55, the 2-pin connector cover has to be connected on the radio or the locking bracket has to be attached to the external speaker microphone.

JVCケンウッド USA Corporation
Communications Sector Headquarters
1440 Corporate Drive | Irving, TX 75038

Order Administration/Distribution
P.O. BOX 22745, 2201 East Dominguez St., Long Beach, CA 90801-5745
www.kenwood.com/usa

JVCケンウッド Canada Inc.
Sede central y distribución canadiense
6070 Kestrel Road, Mississauga, Ontario, Canada L5T 1S8
www.kenwood.com/ca

KENWOOD Communications
Global Website



comms.kenwood.com



ISO9001 Registered
Communications Systems Business Unit
JVCケンウッド Corporation
ADS#30919 Print in U.S.A.