

NX-740(H)/840(H)

NEXEDGE®

NEXEDGE® VHF/UHF Digital & FM Mobile Radios

NXDN® FleetSync®

GENERAL FEATURES

- 50 W (136-174 MHz) Model
- 45 W (450-520 MHz) Model
- Max. 16 CH per Zone
- 2 Conventional Zones
- 2-Digit LED Channel Display
- Function/Status LED Dots
- Backlit Keys
- Transmit /Busy / Call Alert LED
- Blue Function/Status LED
- 9 Programmable Function Keys
- Emergency / AUX Key
- 4W Speaker Audio
- Voice CH# Announcement
- DB15 Accessory Interface
- 8 Programmable I/O Ports
- KPG-175D Windows® FPU
- MIL-STD-810 C/D/E/F
- IP-54 Water & Dust Intrusion
- PC Serial Interface
- GPS Receiver Option

DIGITAL COMMON

- NXDN® Digital Air Interface
- AMBE+2™ VOCODER
- 6.25 kHz Channels
- Over-the-Air Alias (TX Only)
- Paging Call
- Emergency Call
- All Group Call
- Status Messaging
- Remote Stun/Kill
- Remote Check
- GPS Location with Voice
- NXDN® Scrambler Included

DIGITAL CONVENTIONAL MODE

- 64 Radio Access Numbers (RAN)
- Individual & Group Selective Call
- Conventional IP Networks
- Site Roaming

SCAN

- Single Zone Scan
- Single Priority Scan

ANALOG MODE - GENERAL

- 12.5 kHz Channels
- Conventional Zones
- FleetSync®, MDC-1200, DTMF
- QT/DQT/Two-Tone
- Voice Inversion Scrambler (16 Codes)

FleetSync®

- PTT ID ANI
- Selective / Group Call
- Emergency Status
- Send GPS Data

MDC-1200

- PTT ID ANI
- Emergency, Radio Check & Inhibit



Options





■ KES-3 External Speaker



KCT-36 3m Extension Cable (for KCT-60)



■ KMB-10 Key Lock Adapter







■ KES-5 External Speaker (requires KCT-60 option)



■ KCT-60 DB 15-to-15 Pin Molex Adaptor Cable



■ KMB-24 Mounting Case for KPS-15



■ KMC-36 Microphone with Keypad

■ KMC-35 Microphone (Supplied)



KCT-18 Ignition Sense Cable (Requires KCT-60 option)



Line Filter



KPS-15 DC Power Supply

Contact an authorized Kenwood dealer for details and complete list of all accessories and options.



All accessories and options may not be available in all markets.

4K00F1D, 4K00F7W, 4K00F2D

Main Specifications

NX-740(H) GENERAL 450-520 MHz Frequency Range 136-174 MHz **Number of Channels** Max. 32 Max. Channels per Zone 16 12.5 kHz **Channel Spacing** Analog 6.25 kHz **Operating Voltage** 13.6 V DC ± 15% -22° F to +140° F (-30° C to +60° C) **Operating Temperature Range Frequency Stability** ± 1.0 ppm Antenna Impedance 50 Ω 6.30 x 1.69 x 4.83 in (160 x 43 x 122.6 mm) Dimensions (W x H x D) Projections not included Weight (net) 2.42 lb (1.10 kg) FCC ID K44452600 K44452700

Measurements made per TIA/EIA 603 and specifications shown are typical. Digital measurements made per CAI measurement procedure.

Specifications are subject to change without notice, due to advancements in technology.

FleetSync® is a registered trademark of JVCKENWOOD Corporation. AMBE+2™ is a trademark of Digital Voice Systems Inc.

Windows® is a registered trademark of Digital voice Systems inc.

NXDN® is a trademark of VICKENWOOD Corporation and Icom Inc.

NEXEDGE® is a trademark of JVCKENWOOD Corporation.

		NX-740(H)	NX-840(H)	
RECEIVER				
Sensitivity	Digital	0.28 μV		
	Analog (12 dB SINAD)	0.28	μV	
Selectivity	Analog @ 25 kHz	65 dB		
Intermodulation	Analog	75 dB		
Spurious Response	Analog	75 dB		
Audio Output		4W with less than 5 % distortion		
TRANSMITTER				
RF Power Output	High / Mid / Low	50-25-5 W	45-25-5 W	
Spurious Response		70 dB		
FM Hum & Noise	Analog	40 dB		
Audio Distortion		Less than 5%		
Modulation		11K0F3E, 4K00F1E,		

ACCESSORIES INCLUDED

- KMC-30 Microphone
- DC Cable
- Fuse
- Set of screws
- Mic. Hanger
- Bracket

Supplied accessories may vary depending on the market.

Applicable MIL-STD & IP

MIL Standard	MIL 810C Methods/Procedures	MIL 810D Methods/Procedures	MIL 810E Methods/Procedures	MIL 810F Methods/Procedures	MIL 810G Methods/Procedures
Low Pressure	500.1/Procedure I	500.2/Procedure I, II	500.3/Procedure I, II	500.4/Procedure I, II	500.5/Procedure I, II
High Temperature	501.1/Procedure I, II	501.2/Procedure I, II	501.3/Procedure I, II	501.4/Procedure I, II	501.5/Procedure I, II
Low Temperature	502.1/Procedure I	502.2/Procedure I, II	502.3/Procedure I, II	502.4/Procedure I, II	502.5/Procedure I, II
Temperature Shock	503.1/Procedure I	503.2/Procedure I	503.3/Procedure I	503.4/Procedure I, II	503.5/Procedure I
Solar Radiation	505.1/Procedure I	505.2/Procedure I	505.3/Procedure I	505.4/Procedure I	505.5/Procedure I
Rain*	506.1/Procedure I, II	506.2/Procedure I, II	506.3/Procedure I, II	506.4/Procedure I, III	506.5/Procedure I, III
Humidity	507.1/Procedure I, II	507.2/Procedure II, III	507.3/Procedure II, III	507.4	507.5/Procedure II
Salt Fog*	509.1/Procedure I	509.2/Procedure I	509.3/Procedure I	509.4	509.5
Dust*	510.1/Procedure I	510.2/Procedure I	510.3/Procedure I	510.4/Procedure I, III	510.5/Procedure I
Vibration	514.2/Procedure VIII, X	514.3/Procedure I	514.4/Procedure I	514.5/Procedure I	514.6/Procedure I Cat.20
Shock	516.2/Procedure I, II, III, V	516.3/Procedure I, IV, V	516.4/Procedure I, IV, V	516.5/Procedure I, IV, V	516.6/Procedure I, IV, V
International Protection Standard					
Dust & Water Protection	IP54*			•	•

^{*}Required conditions; Microphone (KMC-35 or KMC-36) is connected: Cap shall be installed on the speaker connector; Cover shall be installed at D-sub connector (15pin); and KCT cable and/or SP cable are not connected

KENWOOD

Kenwood U.S.A. Corporation

Communications Sector Headquarters 3970 Johns Creek Court, Suite 100, Suwanee, GA 30024-1265

Order Administration/Distribution

P.O. BOX 22745, 2201 East Dominguez St., Long Beach, CA 90801-5745



